

09-05-00

A

Please type a plus sign (+) inside this box



PTO/SB/05 (4/98)

Approved for use through 09/30/2000. OMB 0651-0032

Patent and Trademark Office: U.S. DEPARTMENT OF COMMERCE

Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it displays a valid OMB control number

UTILITY PATENT APPLICATION TRANSMITTAL

(Only for new nonprovisional applications under 37 CFR 1.53(b))

Attorney Docket No.	004589.P003
First Inventor or Application Identifier	Alan Lasneski
Title	METHOD AND APPARATUS FOR NOISE REDUCTION USING CAPTURED IMAGES
Express Mail Label No.	EL034440050US

APPLICATION ELEMENTS

See MPEP chapter 600 concerning utility patent application contents

ADDRESS TO:

 Assistant Commissioner for Patents
 Box Patent Application
 Washington, DC 20231

1. ☒ Fee Transmittal Form
(Submit an original, and a duplicate for fee processing)
2. ☒ Specification [Total Pages 29]
(preferred arrangement set forth below)
 - Descriptive title of the Invention
 - Cross References to Related Applications
 - Statement Regarding Fed sponsored R & D
 - Reference to Microfiche Appendix
 - Background of the Invention
 - Brief Summary of the Invention
 - Brief Description of the Drawings (if filed)
 - Detailed Description
 - Claim(s)
 - Abstract of the Disclosure
3. ☒ Drawing(s) (35 U.S.C. 113) [Total Sheets 9]
4. Oath or Declaration [Total Pages 3]
 - a. ☒ Newly executed (original copy)
 - b. ☐ Copy from a prior application (37 C.F.R. § 1.63(d))
(for continuation/divisional with Box 16 completed)
 - i. ☐ DELETION OF INVENTOR(S)
Signed statement attached deleting inventor(s) named in the prior application, see 37 CFR §§ 1.63(d)(2) and 1.33(b).

5. ☐ Microfiche Computer Program (Appendix)
6. Nucleotide and/or Amino Acid Sequence Submission
(if applicable, all necessary)
 - a. ☐ Computer Readable Copy
 - b. ☐ Paper Copy (identical to computer copy)
 - c. ☐ Statement verifying identity of above copies

ACCOMPANYING APPLICATION PARTS

7. ☒ Assignment Papers (cover sheet & document(s))
8. ☐ 37 C.F.R. § 3.73(b) Statement ☐ Power of Attorney
(when there is an assignee)
9. ☐ English Translation Document (if applicable)
10. ☐ Information Disclosure Statement (IDS)/PTO - 1449 ☐ Copies of IDS Citations
11. ☐ Preliminary Amendment
12. ☒ Return Receipt Postcard (MPEP 503)
(Should be specifically itemized)
13. ☐ *Small Entity Statement(s) ☐ Statement filed in prior application, Status still proper and desired
14. ☐ Certified Copy of Priority Document(s)
(if foreign priority is claimed)
15. ☐ Other: _____

***NOTE FOR ITEMS 1 & 13: IN ORDER TO BE ENTITLED TO PAY SMALL ENTITY FEES, A SMALL ENTITY STATEMENT IS REQUIRED (37 C.F.R. § 1.27), EXCEPT IF ONE FILED IN A PRIOR APPLICATION IS RELIED UPON (37 C.F.R. § 1.28).**

16. If a CONTINUING APPLICATION, check appropriate box, and supply the requisite information below and in a preliminary amendment:

☐ Continuation ☐ Divisional ☐ Continuation-in-part (CIP) of prior application No: _____

Prior application Information: Examiner _____ Group/Art Unit: _____

For CONTINUATION or DIVISIONAL APPS only: The entire disclosure of the prior application, from which an oath or declaration is supplied under Box 4b, is considered a part of the disclosure of the accompanying continuation or divisional application and is hereby incorporated by reference. The incorporation can only be relied upon when a portion has been inadvertently omitted from the submitted application parts.

17. CORRESPONDENCE ADDRESS

☐ Customer Number of Bar Code Label ☐ (Insert Customer No. or Attach bar code label here) or ☒ Correspondence address below

Name	BLAKELY, SOKOLOFF, TAYLOR & ZAFMAN LLP				
Address	12400 Wilshire Boulevard, Seventh Floor				
City	Los Angeles	State	California	Zip Code	90025
Country	U.S.A.	Telephone	(503) 684-6200	Fax	(503) 684-3245

Name (Print/Type) Donna Jo Coningsby, Reg. No. 41,684

Signature

Donna Jo Coningsby

Date 08/31/00

Burden Hour Statement: This form is estimated to take 2 hours to complete. Time will vary depending upon the needs of the individual case. Any comments on the amount of time you are required to complete this form should be sent to the Chief Information Officer, Patent and Trademark Office, Washington, DC 20231. DO NOT SEND FEES OR COMPLETED FORMS TO THIS ADDRESS. SEND TO: Assistant Commissioner for Patents, Box Patent Application, Washington, DC 20231.

Please type a plus sign (+) inside this box → +

PTO/SB/17 (6/99)
Approved for use through 09/30/2000 OMB 0651-0032
Patent and Trademark Office, U.S. DEPARTMENT OF COMMERCE

Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it displays a valid OMB control number

<h2 style="margin: 0;">FEE TRANSMITTAL for FY 1999</h2> <p style="font-size: small; margin: 5px 0;">Patent fees are subject to annual revision. Small Entity payments must be supported by a small entity statement, otherwise large entity fees must be paid. See Forms PTO/SB/09-12. See 37 C.F.R. §§ 1.27 and 1.28.</p>		<p style="margin: 0;"><i>Complete if Known</i></p> <table border="1" style="width: 100%; border-collapse: collapse;"> <tr> <td style="width: 50%;">Application Number</td> <td style="width: 50%;"></td> </tr> <tr> <td>Filing Date</td> <td>August 31, 2000</td> </tr> <tr> <td>First Named Inventor</td> <td>Alan Lasneski</td> </tr> <tr> <td>Examiner Name</td> <td></td> </tr> <tr> <td>Group/Art Unit</td> <td></td> </tr> <tr> <td>Attorney Docket No.</td> <td>004589.P003</td> </tr> </table>		Application Number		Filing Date	August 31, 2000	First Named Inventor	Alan Lasneski	Examiner Name		Group/Art Unit		Attorney Docket No.	004589.P003
Application Number															
Filing Date	August 31, 2000														
First Named Inventor	Alan Lasneski														
Examiner Name															
Group/Art Unit															
Attorney Docket No.	004589.P003														
TOTAL AMOUNT OF PAYMENT	(\$)	886.00													

10796 U.S. PTO
 09/653613
 08/31/00

<h3 style="margin: 0;">METHOD OF PAYMENT (check one)</h3> <p>1. <input type="checkbox"/> The Commissioner is hereby authorized to charge indicated fees:</p> <p>2. <input checked="" type="checkbox"/> The Commissioner is hereby authorized to credit any over payments to:</p> <p>Deposit Account Number: 02-2666</p> <p>Deposit Account Name: Blakely, Sokoloff, Taylor & Zafman LLP</p> <p><input checked="" type="checkbox"/> Charge Any Additional Fees Required Under 37 CFR §§ 1.16, 1.17, 1.18 and 1.20</p> <p>3. <input checked="" type="checkbox"/> Payment Enclosed:</p> <p><input checked="" type="checkbox"/> Check <input type="checkbox"/> Money Order <input type="checkbox"/> Other</p>	<h3 style="margin: 0;">FEE CALCULATION (continued)</h3> <h4 style="margin: 0;">3. ADDITIONAL FEE</h4> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th colspan="2">Large Entity</th> <th colspan="2">Small Entity</th> <th rowspan="2">Fee Description</th> <th rowspan="2">Fee Paid</th> </tr> <tr> <th>Fee Code</th> <th>Fee (\$)</th> <th>Fee Code</th> <th>Fee (\$)</th> </tr> </thead> <tbody> <tr> <td>105</td> <td>130</td> <td>205</td> <td>65</td> <td>Surcharge - late filing fee or oath</td> <td></td> </tr> <tr> <td>127</td> <td>50</td> <td>227</td> <td>25</td> <td>Surcharge - late provisional filing fee or cover sheet.</td> <td></td> </tr> <tr> <td>139</td> <td>130</td> <td>139</td> <td>130</td> <td>Non-English specification</td> <td></td> </tr> <tr> <td>147</td> <td>2,520</td> <td>147</td> <td>2,520</td> <td>For filing a request for reexamination</td> <td></td> </tr> <tr> <td>112</td> <td>920*</td> <td>112</td> <td>920*</td> <td>*Requesting publication of SIR prior to Examiner action</td> <td></td> </tr> <tr> <td>113</td> <td>1,840*</td> <td>113</td> <td>1,840*</td> <td>*Requesting publication of SIR after Examiner action</td> <td></td> </tr> <tr> <td>115</td> <td>110</td> <td>215</td> <td>55</td> <td>Extension for response within first month</td> <td></td> </tr> <tr> <td>116</td> <td>380</td> <td>216</td> <td>190</td> <td>Extension for response within second month</td> <td></td> </tr> <tr> <td>117</td> <td>870</td> <td>217</td> <td>435</td> <td>Extension for response within third month</td> <td></td> </tr> <tr> <td>118</td> <td>1,210</td> <td>218</td> <td>680</td> <td>Extension for response within fourth month</td> <td></td> </tr> <tr> <td>128</td> <td>1,850</td> <td>228</td> <td>925</td> <td>Extension for response within fifth month</td> <td></td> </tr> <tr> <td>119</td> <td>300</td> <td>219</td> <td>150</td> <td>Notice of Appeal</td> <td></td> </tr> <tr> <td>120</td> <td>300</td> <td>220</td> <td>150</td> <td>Filing a brief in support of an appeal</td> <td></td> </tr> <tr> <td>121</td> <td>260</td> <td>221</td> <td>130</td> <td>Request for oral hearing</td> <td></td> </tr> <tr> <td>138</td> <td>1,510</td> <td>138</td> <td>1510</td> <td>Petition to institute a public use proceeding</td> <td></td> </tr> <tr> <td>140</td> <td>110</td> <td>240</td> <td>55</td> <td>Petition to revive - unavoidable</td> <td></td> </tr> <tr> <td>141</td> <td>1,210</td> <td>241</td> <td>605</td> <td>Petition to revive - unintentional</td> <td></td> </tr> <tr> <td>142</td> <td>1,210</td> <td>242</td> <td>605</td> <td>Utility issue fee (or reissue)</td> <td></td> </tr> <tr> <td>143</td> <td>430</td> <td>243</td> <td>215</td> <td>Design issue fee</td> <td></td> </tr> <tr> <td>144</td> <td>580</td> <td>244</td> <td>290</td> <td>Plant issue fee</td> <td></td> </tr> <tr> <td>122</td> <td>130</td> <td>122</td> <td>130</td> <td>Petitions to the Commissioner</td> <td></td> </tr> <tr> <td>123</td> <td>50</td> <td>123</td> <td>50</td> <td>Petitions related to provisional applications</td> <td></td> </tr> <tr> <td>126</td> <td>240</td> <td>126</td> <td>240</td> <td>Submission of Information Disclosure Stmt</td> <td></td> </tr> <tr> <td>581</td> <td>40</td> <td>581</td> <td>40</td> <td>Recording each patent assignment per property (times number of properties)</td> <td>40.00</td> </tr> <tr> <td>146</td> <td>790</td> <td>246</td> <td>395</td> <td>Filing a submission after final rejection (37 CFR 1.129(a))</td> <td></td> </tr> <tr> <td>149</td> <td>790</td> <td>249</td> <td>395</td> <td>For each additional invention to be examined (37 CFR 1.129(b))</td> <td></td> </tr> <tr> <td colspan="4">Other fee (specify)</td> <td></td> <td></td> </tr> <tr> <td colspan="4">Other fee (specify)</td> <td></td> <td></td> </tr> <tr> <td colspan="4" style="text-align: right;">* Reduced by Basic Filing Fee Paid</td> <td></td> <td></td> </tr> <tr> <td colspan="4" style="text-align: right;">SUBTOTAL (3)</td> <td>(\$)</td> <td>40.00</td> </tr> </tbody> </table>	Large Entity		Small Entity		Fee Description	Fee Paid	Fee Code	Fee (\$)	Fee Code	Fee (\$)	105	130	205	65	Surcharge - late filing fee or oath		127	50	227	25	Surcharge - late provisional filing fee or cover sheet.		139	130	139	130	Non-English specification		147	2,520	147	2,520	For filing a request for reexamination		112	920*	112	920*	*Requesting publication of SIR prior to Examiner action		113	1,840*	113	1,840*	*Requesting publication of SIR after Examiner action		115	110	215	55	Extension for response within first month		116	380	216	190	Extension for response within second month		117	870	217	435	Extension for response within third month		118	1,210	218	680	Extension for response within fourth month		128	1,850	228	925	Extension for response within fifth month		119	300	219	150	Notice of Appeal		120	300	220	150	Filing a brief in support of an appeal		121	260	221	130	Request for oral hearing		138	1,510	138	1510	Petition to institute a public use proceeding		140	110	240	55	Petition to revive - unavoidable		141	1,210	241	605	Petition to revive - unintentional		142	1,210	242	605	Utility issue fee (or reissue)		143	430	243	215	Design issue fee		144	580	244	290	Plant issue fee		122	130	122	130	Petitions to the Commissioner		123	50	123	50	Petitions related to provisional applications		126	240	126	240	Submission of Information Disclosure Stmt		581	40	581	40	Recording each patent assignment per property (times number of properties)	40.00	146	790	246	395	Filing a submission after final rejection (37 CFR 1.129(a))		149	790	249	395	For each additional invention to be examined (37 CFR 1.129(b))		Other fee (specify)						Other fee (specify)						* Reduced by Basic Filing Fee Paid						SUBTOTAL (3)				(\$)	40.00
Large Entity		Small Entity		Fee Description	Fee Paid																																																																																																																																																																																										
Fee Code	Fee (\$)	Fee Code	Fee (\$)																																																																																																																																																																																												
105	130	205	65	Surcharge - late filing fee or oath																																																																																																																																																																																											
127	50	227	25	Surcharge - late provisional filing fee or cover sheet.																																																																																																																																																																																											
139	130	139	130	Non-English specification																																																																																																																																																																																											
147	2,520	147	2,520	For filing a request for reexamination																																																																																																																																																																																											
112	920*	112	920*	*Requesting publication of SIR prior to Examiner action																																																																																																																																																																																											
113	1,840*	113	1,840*	*Requesting publication of SIR after Examiner action																																																																																																																																																																																											
115	110	215	55	Extension for response within first month																																																																																																																																																																																											
116	380	216	190	Extension for response within second month																																																																																																																																																																																											
117	870	217	435	Extension for response within third month																																																																																																																																																																																											
118	1,210	218	680	Extension for response within fourth month																																																																																																																																																																																											
128	1,850	228	925	Extension for response within fifth month																																																																																																																																																																																											
119	300	219	150	Notice of Appeal																																																																																																																																																																																											
120	300	220	150	Filing a brief in support of an appeal																																																																																																																																																																																											
121	260	221	130	Request for oral hearing																																																																																																																																																																																											
138	1,510	138	1510	Petition to institute a public use proceeding																																																																																																																																																																																											
140	110	240	55	Petition to revive - unavoidable																																																																																																																																																																																											
141	1,210	241	605	Petition to revive - unintentional																																																																																																																																																																																											
142	1,210	242	605	Utility issue fee (or reissue)																																																																																																																																																																																											
143	430	243	215	Design issue fee																																																																																																																																																																																											
144	580	244	290	Plant issue fee																																																																																																																																																																																											
122	130	122	130	Petitions to the Commissioner																																																																																																																																																																																											
123	50	123	50	Petitions related to provisional applications																																																																																																																																																																																											
126	240	126	240	Submission of Information Disclosure Stmt																																																																																																																																																																																											
581	40	581	40	Recording each patent assignment per property (times number of properties)	40.00																																																																																																																																																																																										
146	790	246	395	Filing a submission after final rejection (37 CFR 1.129(a))																																																																																																																																																																																											
149	790	249	395	For each additional invention to be examined (37 CFR 1.129(b))																																																																																																																																																																																											
Other fee (specify)																																																																																																																																																																																															
Other fee (specify)																																																																																																																																																																																															
* Reduced by Basic Filing Fee Paid																																																																																																																																																																																															
SUBTOTAL (3)				(\$)	40.00																																																																																																																																																																																										

SUBMITTED BY				Complete (if applicable)	
Typed or Printed Name	Donna Jo Coningsby			Reg. Number	41,684
Signature				Date	08/31/00
				Deposit Account User ID	02-2666

Burden Hour Statement This form is estimated to take 0.2 hours to complete. Time will vary depending upon the needs of the individual case. Any comments on the amount of time you are required to complete this form should be sent to the Chief Information Officer, Patent and Trademark Office, Washington, DC 20231. DO NOT SEND FEES OR COMPLETED FORMS TO THIS ADDRESS. SEND TO: Assistant Commissioner for Patents, Box Patent Application, Washington, DC 20231

Trans express mail no. EL034440050US

APPLICATION FOR UNITED STATES LETTERS PATENT
FOR
METHOD AND APPARATUS FOR NOISE REDUCTION USING CAPTURED IMAGES

Inventor: Alan Lasneski

Prepared by:

BLAKELY SOKOLOFF TAYLOR & ZAFMAN, LLP
12400 Wilshire Boulevard, 7th Floor
Los Angeles, California 90025
(503) 684-6200

“Express Mail” label number EL034440050US

M & A FOR NOISE REDUCTION
USING CAPTURED IMAGES
EL034440050US DJC/mwb

METHOD AND APPARATUS FOR NOISE REDUCTION USING CAPTURED IMAGES

Background Of The Invention

1. Field of the Invention

The present invention relates generally to reducing phase noise and distortion in the conversion of an analog video signal to a digital video signal. In particular, the present invention is directed to technology that reduces phase noise and distortion in the digitally converted image by selectively capturing reference frames of the image in accordance with a change threshold.

2. Background Information

Presentations using multimedia projection display systems have become popular for purposes such as sales demonstrations, business meetings, and classroom sessions. In a common mode of operation, multimedia projection display systems receive analog video signals from a multimedia device such as a personal computer (PC). The video signals represent still, partial-, or full-motion display images of the type rendered by the PC. The analog video signals are converted into digital video signals to control a digitally-driven display object, such as a transmissive liquid crystal display (LCD) or digital mirror device (DMD), to form the display images for projection onto a display screen.

Two common types of multimedia projection display systems are LCD projectors and LCD projection panels. An LCD projector includes a transmissive LCD, a light source, and projection optics to form and project display images in the manner described above. An LCD projection panel includes a similar transmissive LCD to form

the display image, but operates with a conventional overhead projector (OHP) having a light source and projection optics, to project the display image onto a display screen.

Examples of such LCD projectors and LCD projection panels are sold under the respective trademarks LITEPRO and PANELBOOK by In Focus Systems, Inc. of

5 Wilsonville, Oreg., the assignee of the present application.

Because the LCDs and DMDs used in multimedia projection display systems require digital video signals, the multimedia projection display system normally has an analog to digital (A/D) signal converter for converting the PC-generated analog video signals into a digital format suitable for driving the LCD, DMD or other type of display object.

10 The PC-generated analog video signal is actually comprised of three analog image data signals, one for each of the primary colors, red, green and blue, and a digital timing signal, which may include a pulsed horizontal synchronizing signal (H_{sync}) as well as a pulsed vertical synchronizing signal (V_{sync}), or a composite sync signal. The individual analog image data signals representing the colors are generated from bit data in a memory portion of the PC, using three digital-to-analog (D/A) converters, one for each of the colors, red, green, and blue.

15 A complete image is typically displayed during a time interval known as a "video frame period." With reference to Fig. 4, each video frame 9 is usually produced to have a central active video region 11 surrounded by an inactive ("blanked") margin 13. The central active video region 11 is composed of a number of horizontal and vertical picture elements (pixels), typically ranging from 640 X 480 pixels to 1600 X 1200 pixels, referred to as the display resolution mode. As the image changes the pixels are activated on and off, with the central active video region 11 being refreshed at rates of
20 60 to 100 Hz, as dictated by the constraints of the display object (e.g. the LCD, DMD, etc.) used in the multimedia projection display system. Since compatibility with the

various PC display resolution modes is a desirable feature for multimedia projection display systems, the A/D signal converter typically includes an interface that is capable of converting analog video signals having a variety of resolution modes.

The A/D signal converter is usually combined with a phase-locked loop (PLL), which may comprise a phase comparator, a low-pass loop filter, and a voltage-controlled oscillator (VCO) formed in a loop to generate a feedback signal that locks into the H_{sync} pulsed horizontal synchronizing signal. In order to generate a selected multiple n of pixel clock pulses for each period of H_{sync} , a divide-by- n counter is added to the feedback loop between the VCO output and the phase comparator.

An example of a pixel clock waveform 4 is shown in FIG. 1. The number n of individual pixel clock pulses per H_{sync} pulse may be set by reference to the resolution mode of the analog video source. To set the resolution mode, certain characteristics of the analog video signal, such as H_{sync} and V_{sync} , may be used to refer to a resolution mode look-up table stored in the projection display system's CPU. The number n should be set to equal the number of pixel data components in each horizontal line of the scanned analog signal, including those in the central active video region 11 and the blanked margin regions 13 (see FIG. 4) on either side of the central active video region 11. For example, for a screen resolution of 640 X 480, the number n may be set at about 800 to include the blanked regions 13 on either side of the 640 pixel-wide central active video region 11. Thus, the pixel clock would sample the continuous stream of analog image data 800 times along each horizontal line of the frame.

FIG. 1 further shows the desired relationship between the analog video data signal 1 and the pixel clock signal 4. The number n of pixel clocks 5 is set to establish a one-to-one relationship between pixel clock pulses 5 and pixel data components 2 of the analog data signal 1. This one-to-one relationship requires that the pixel clock signal frequency be equal to the analog video data signal frequency. Under this relationship,

each pixel data component 2 of the analog signal is sampled by a single pixel clock pulse 5, which reads the instantaneous voltage value of the pixel data component so that it can be digitized. The stream of digitized instantaneous voltage values form the digital video data signal, which is addressed to the LCD, DMD, or other type of display object, to appropriately set pixels to blank (black) or to selected activated (non-black) status to replicate the image defined by the analog video data signal.

One problem with the above-described A/D conversion is that it is often imperfect due to errors in the pixel clock sampling of the analog signal. With reference to FIG. 1, since the pixel clock pulses 5 have "jitter" zones 6 at their leading and trailing edges, the clock pulses 5 should be registered with the centers of the pixel data components 2, so that the sampling is not randomly pushed by the jitter into the transition regions 3 of the analog video data signal 1. If the pixel clock pulses 5 are not properly registered, the resulting sampling imprecision gives rise to frequency (also know as "tracking") and "phase" errors, both of which introduce noise that may degrade the quality of the LCD, DMD, or other display object's image.

FIG. 2 illustrates a tracking error that results from the improperly setting of the number n of pixel clocks. As discussed above, the number n of pixel clocks should be equal to the number of pixel data components 2 of each horizontal line of analog video data signal 1. As illustrated, the improper setting of n results in the pixel data components 2 not being sampled at a consistent point. Specifically, n is set too large in clock signal 4' (i.e. the clock signal frequency is too high). The resulting crowding of the pixel clock pulses 5' yields an additive leftward drift of the pixel clock pulses 5' relative to the pixel data components 2 of the analog video data signal 1. Such drift causes sampling in the transition regions 3. For instance, as indicated by positional bracket A, the leading edges 7' of the third through the sixth clock pulses 5' sample in transition zones 3 of the analog video data signal 1. Accordingly, the transition zone data will be

erroneous and the image information from adjacent non-sampled pixel data components 2 will be missing from the digitized video signal. If n is erroneously set large enough, the pixel clock pulses may be so crowded that individual analog pixel data components 2 may be double-sampled. On the other hand, if n is erroneously set too small (i.e. the pixel clock signal frequency is too low), the dispersion of the pixel clock pulses results in a rightward drift wherein sampling may also occur in the transition regions. In all of these cases, the erroneous sampling provides erroneous video signal data that generates unwanted distortion that degrades the LCD or other display object video image quality.

FIG. 3 illustrates that phase error may occur even when the pixel clock signal frequency equals the analog video data signal frequency (i.e. even when there is no tracking error). For example, as shown in pixel clock signal 4" in **FIG. 3**, the clock phase may be erroneously set such that every pixel clock pulse samples a transition region 3 of the analog video data signal. Leading edge jitter makes such phase error more likely, since if the jitter zones 6" straddle the intersections 8 of the pixel data components 2 and transition regions 3 of the analog video data signal 1, the voltage will be randomly sampled on either side of the intersection 8. In any case, phase error is undesirable since it generates unwanted phase noise, or "snow" in the LCD, DMD, or other display object video image.

Prior art techniques for reducing noise have focused on providing feedback to the pixel clock in order to eliminate the above-described tracking and phase errors. For example, a current projection display system may include an image capture circuit that automatically eliminates phase and tracking errors by monitoring the actual active image width of the analog video data signal measured by the number n of pixel clocks, and adjusting the frequency and phase components of the pixel clock signal until the expected width of the image matches the actual width. A current projection display

system may also include an image capture circuit that automatically eliminates phase and tracking errors by monitoring a selected pixel data component at the edge of the central active video region that is horizontally stationary from frame to frame of the analog video data, and automatically iteratively adjusting the pixel clock pulse until a
5 pixel clock pulse is centrally registered with the selected pixel data component. Both of these prior art techniques used in current projection display systems are described in U.S. Pat. Nos. 5,767,916 and 5,805,233, assigned to In Focus Systems, Inc. of Wilsonville, Oreg., the assignee of the present invention.

The image capture circuit of a current projection display system includes a programmable delay device, a PLL, a divide-by-n-counter, an A/D converter, and an ASIC (Application Specific Integrated Circuit) that contains the image edge or width
10 detection circuitry that provides the feedback necessary to correct the pixel clock.

In operation, the A/D converter samples (reads) the instantaneous voltage value of the analog video data signal at the leading edge of each of the pixel clocks, thereby
15 generating a series of sampled data signal values. The A/D converter then quantizes the sampled values by matching each value to one of a series of preselected voltage amplitude levels, which have corresponding numerical values. The numerical values are represented digitally and coded to establish 8-bit data for each of the colors, red, green, and blue. The three eight-bit color data signals are input through the three
20 respective color data signal channels to the ASIC. A window random access memory (WRAM) is connected between the ASIC and the LCD, DMD, or other display object that ultimately receives the output from the A/D converter. At the display object, the coded color data signals set pixels to blank (black) or to specific activated (non-black) status corresponding to the sampled voltage level. A microcontroller, which is part of
25 the current projection display system CPU, uses the feedback provided by the ASIC to

control the programmable delay device and divide-by-n-counter to change the pixel clock settings and eliminate the phase and tracking errors.

Despite the above-described improvements in eliminating phase and tracking errors, current projection display systems are still not optimum. Particularly frustrating is the fact that the causes of the phase noise and distortion may dynamically change as the environment changes. Thus, any given technique for reducing or eliminating the distortion may or may not be effective from one moment to the next.

Another problem is that a digitized video frame representing the complete image displayed during the video frame period must be stored within the WRAM until it is transmitted to the display object. Since the video frames are typically stored in WRAM at a faster rate than they are transmitted to the display object, the WRAM must include enough frame buffer capacity or memory to store a number of video frames at once. For example, each video frame may be stored to the WRAM at the rate of 80 Hz (i.e. 80 frames per second), but may only be output to the display object at the rate of 60 Hz, as dictated by the refresh rate of the particular display object (e.g. the LCD, DMD, etc.).

For even the lowest resolution video display systems, storing video frames in WRAM results in the storage of a significantly large amount of data. Since a video frame represents the complete image, it contains data representing every pixel in the central active video region. The optical state of each pixel in the central active video region, i.e. its color or shade of gray, is described by several bits of data; the exact number of bits depends upon the desired number of colors or shades of gray that are to be displayed. For example, a typical LCD may have 480 rows and 640 columns that intersect to form a matrix of 307,200 pixels corresponding to the pixels in the central active video region. Consequently, if 8 bits are required to specify each of the three colors comprising each pixel, then 921,600 bytes of image data (3 bytes X 307,200

pixels), or nearly 1 megabyte, are required to characterize a single digitized video frame.

The problem of having to provide a necessarily large WRAM storage capacity is compounded by the fact that the WRAM is expensive, which adds significantly to the cost of the multimedia projection display system. Additionally, the WRAM takes up a large amount of board space. Moreover, the sheer volume of digitized video frames generated by the multimedia projection display system requires a significantly large transmission bandwidth between the WRAM and the LCD, DMD, or other display object. Large transmission bandwidth requirements present a problem when designing networked presentation projector applications. For example, in a wireless network environment, including wireless networks designed in accordance with the IEEE 802.11 Wireless LAN Standard, or the Draft Specification of Bluetooth: A Global Specification for Wireless Connectivity, promulgated by the Bluetooth Special Interest Group, or even in a conventional networked environment where the LCD, DMD, or other display object is capable of providing its own frame memory, it is desirable to reduce the transmission bandwidth requirements where possible to enable the development of networked presentation projector applications.

Accordingly, it is desirable to provide a multimedia projection display system that not only reduces the noise and distortion in the digitally sampled image, but also reduces the transmission bandwidth requirements between the WRAM and the display object.

SUMMARY

According to one aspect of the invention, a method is provided in which a digitally converted image is displayed free of phase noise and distortion and using a reduced amount of stored frame memory by displaying only a selected subset of the video frames that represent the digitally converted image. The selected subset is comprised

of reference video frames, where a new reference frame is captured for display only after determining that a pixel of an inbound video frame exceeds a certain threshold of change as compared to a corresponding pixel of the previously captured reference frame.

5 In accordance with other aspects of the present invention, apparatus are provided for carrying out the above and other methods.

BRIEF DESCRIPTION OF DRAWINGS

The present invention will be described by way of exemplary embodiments, but not limitations, illustrated in the accompanying drawings in which like references denote similar elements, and in which:

FIG. 1 depicts an analog video data signal waveform and a pixel clock signal waveform in a desired relationship where no tracking or phase error would be result.

FIG. 2 depicts an analog video data signal waveform and a pixel clock signal waveform in a relationship where tracking error would result.

FIG. 3 depicts an analog video data signal waveform and a pixel clock signal waveform in a relationship where phase error would result.

FIG. 4 depicts an exemplary video display, showing a central active video region surrounded by an inactive margin region.

FIG. 5 is an overall schematic view of a multimedia source connected to a multimedia projection display system, further depicting a reference frame capture circuit in accordance with one embodiment of the present invention.

FIG. 6 is a schematic view of a phase-locked-loop (PLL) circuit used in analog video signal capture in accordance with one embodiment of the present invention.

FIG. 7 schematically depicts a pixel value calculator in accordance with one embodiment of the present invention.

FIG. 8 is an block diagram of the logical components of the reference frame capture circuit shown in **FIG. 5**, in accordance with one embodiment of the invention.

FIG. 9 is a flow diagram showing a reference frame capture method used in the reference frame capture circuit shown in **FIG. 5**, in accordance with one embodiment of the present invention.

FIG. 10 illustrates an example implementation in the form of a tabulation of a series of inbound frames and lines and the corresponding pixel value comparisons and resulting actions in accordance with one embodiment of the present invention.

FIG. 11 illustrates a pixel value comparison of individual red, green, and blue pixel values in decimal notation in accordance with one embodiment of the present invention.

DETAILED DESCRIPTION OF THE INVENTION

In the following description various aspects of the present invention, a method and apparatus for reducing phase noise and distortion in a digitally converted image, will be described. Specific details will be set forth in order to provide a thorough understanding of the present invention. However, it will be apparent to those skilled in the art that the present invention may be practiced with only some or all of the described aspects of the present invention, and with or without some or all of the specific details. In some instances, well known features may be omitted or simplified in order not to obscure the present invention.

Various operations will be described as multiple discrete steps performed in turn in a manner that is most helpful in understanding the present invention. However, the order of description should not be construed as to imply that these operations are necessarily performed in the order they are presented, or even order dependent. Lastly, repeated

usage of the phrase “in one embodiment” does not necessarily refer to the same embodiment, although it may.

Devices that generate digitally converted images generally refresh the screen display at rates of 60 –80 Hz (60-80 frames per second) or more to provide a quality image and to avoid eye fatigue. However, the human eye perceives only a portion of the frames, approximately one every 16 milliseconds, or about 1/6th of the frames displayed at 60 Hz. Therefore, it is possible to reduce the number of frames sent to the device without impairing the perceived quality of the image. A reduction in the number of frames sent to the device is particularly desirable in a wireless network environment, or where the device is capable of providing its own frame memory, as it reduces the amount of bandwidth necessary to transmit the frame data between the multimedia projection display system and the display object.

The method of the present invention is based in part on the observation that selectively sending new frames only when there is a perceptively significant change in the frame data not only reduces the number of frames sent to the device, thereby reducing bandwidth requirements, but also improves the overall quality of the perceived image by eliminating unnecessary phase noise and distortion in the digitally converted image.

Referring now to **FIG. 5**, wherein an overall schematic view of a multimedia source connected to a multimedia projection display system depicting a reference frame capture circuit in accordance with one embodiment of the present invention is illustrated. As shown, the projection display system 10 includes an image capture circuit 14 that automatically eliminates phase noise, tracking error, and image distortion. A microcontroller 16, which is part of a display system CPU 17, controls the image capture circuit 14. In the illustrated embodiment, the image capture circuit 14 includes a programmable delay device 18, a PLL 20, a divide-by-n-counter (counter) 22, an A/D

converter 24, and an ASIC (Application Specific Integrated Circuit) that contains an image edge detection circuit 26 and the reference frame capture circuit 27. The microcontroller 16 executes a firmware program that runs the ASIC circuits 26 and 27.

Turning to the signal path to the display object, such as an active matrix LCD 28, shown in **FIG. 5**, the line advance conductor 53, the digital video data signal channels 56a, 56b, 56c, and the frame advance conductor 58 are connected to an input port of a window random access memory (WRAM) 132. The WRAM has an output port connected to a display object control module 134, which in turn is connected to the LCD, DMD, or other display object 28. The connection between the WRAM output port and the display object control module 134 and LCD, DMD, or other display object 28, may be a conventional wired connection or a wireless network connection including, for example, a wireless network connection designed in accordance with the IEEE 802.11 Wireless LAN Standard or in accordance with the Draft Specification of Bluetooth: A Global Specification for Wireless Connectivity, promulgated by the Bluetooth Special Interest Group. The LCD is preferably a 6.4 inch active matrix LCD, such as model LQ64P311 made by Sharp.

Based on the output of the edge detection circuit 26 the microcontroller 16 further controls the delay device 18 and the counter 22 to eliminate phase noise and tracking errors. Based on the output of the reference frame capture circuit 27, the microcontroller 16 further controls the capture to frame memory in WRAM 132 of a reference frame from the frames output from the A/D converter 24 so as to eliminate phase noise and image distortion. The number of reference frames captured depends on the type of image being processed and a threshold setting such that the rate of capture of a reference frame is lower when the image is static (e.g. fixed image presentations) , and higher when the image is dynamic (e.g. full motion video). The threshold setting is pre-selected to provide for the maximum elimination of phase noise

and distortion, while providing a sufficient number of reference frames for proper replication of the digitally converted image at the display object 28. It should be understood that the outputs of the edge detection circuit 26 and reference frame capture circuit 27 are both independent and complementary such that the reference frame capture circuit 27 may be used alone or in combination with the edge detection circuit 26 or other methods to improve the quality of the digitally converted image displayed by the display object 28.

As shown in **FIG. 5**, for purposes of video signal transmission, the multimedia source 12 is connected to the projection display system 10 through a video source cable 30 which is shown in exploded schematic form. The cable 30 is of conventional design and includes multiple distinct conductors that are shielded together, including three separate channels 32a, 32b, 32c for carrying analog signals corresponding to red, green, and blue (RGB) color video components, and two conductors 34, 36 carrying the H_{sync} and V_{sync} signals, respectively.

Turning to the details of the image capture circuit 14, the microcontroller 16 is connected to the delay device 18 by a bus 38, to the counter 22 by a bus 40, and to the ASIC 26 by a bus 42. A mode identification counter 43, which is connected to H_{sync} and V_{sync} through conductors 45 and 47, respectively, may be located in the microcontroller or the ASIC. The mode identification counter 43 may also be provided independent of the microcontroller. A preferred microcontroller 16 is model MC6833 1, made by Motorola. The delay device has an input connected to the H_{sync} conductor 34, and an output connected to the PLL through conductor 44. The preferred delay device is model No. DS10205-25, made by the Dallas Corporation.

As shown in detail in **FIG. 6**, the PLL 20 is of conventional design and includes a phase comparator 46, a low-pass filter 48, and a VCO pixel clock signal generator 50. A feedback loop 52 provided with the counter 22 connects the VCO output 55 and the

phase comparator 46. The counter output 51 is connected to the ASIC 26 through a conductor 53, and the VCO output 55 is connected to the ASIC 26 and the A/D converter 24 through conductor 54. The preferred PLL is model ICS 1522 made by ICS. The counter is preferably a part of the ASIC 26.

5 Referring again to **FIG. 5**, the three analog video data signal channels 32a, 32b, 32c are connected to the A/D converter input. The A/D converter 24 includes three separate conventional A/D converters for digitizing each of the red, green and blue analog video data signals. Three color data signal channels 56a, 56b, 56c connect the A/D converter output to the ASIC 26 and 27. A preferred A/D converter is model 9542A made by the Raytheon Corporation. The V_{sync} signal (frame advance signal) output of the multimedia source 12 is connected to the ASIC 26 and 27 through a frame advance conductor 58.

As shown in detail in **FIG. 7**, a pixel value calculator 97 has inputs receiving each of the RGB video data signal channels 56a, 56b, 56c. The RGB video data signals are connected in parallel to an "OR" gate 99a, and are connected to a 4:1 multiplexer 99b. The output of the OR gate 99a is also connected to the multiplexer 99b. The output 101 of the pixel value calculator 97 is connected through bus 103 to a pixel component value comparator in each of the image edge detection 26 and reference frame capture 27 ASIC circuits.

20 Referring now to **FIG. 8**, wherein a block diagram overview of the functional components of the reference frame capture circuit 27 in accordance with one embodiment of the present invention is illustrated. As shown, the reference frame capture circuit 27 has a microcontroller interface connected to the microcontroller bus 42, and receives inputs from the line advance signal conductor 53, pixel clock signal conductor 54, and the V_{sync} frame advance signal conductor 58. The reference frame capture circuit 27 also receives pixel data input 101 from the color data signal channels

56a, 56b, 56c, through the output 101 of the pixel value calculator 97. Access to a current reference frame in stored frame memory is provided through an input port of the WRAM 132. A horizontal position counter (HPC) component 105 uses input from the line advance conductor 53 and the pixel clock conductor 54 to determine the current
5 pixel position of the pixel data input 101. The reference frame capture circuit 27 receives a threshold value input 110 used by a pixel value comparator component 115 to compare the pixel values of the pixel data input 101 to the corresponding pixel values of the lines of the current reference frame. The reference frame capture circuit 27 further includes a reference frame capture switch 120 to trigger the microcontroller 16 to capture a new reference frame to store in WRAM 132 stored frame memory for eventual transmission to display object 28.

Operation

In operation, the analog video signal is digitized in a manner set forth and described in U.S. Pat. Nos. 5,767,916 and 5,805,233. Referring now to **FIG. 5**, the display system 20 determines the resolution mode by a firmware program that uses the mode identification counter 43. H_{sync} is input through conductor 45 to the mode identification counter 43 and the number of 50 MHz counter clocks over twenty H_{sync} pulses is counted. In this way, an average number of clocks per line is obtained. V_{sync} is input through conductor 47 in the mode identification counter 43 and the number of
20 lines for each V_{sync} pulse is obtained. The firmware then accesses a look-up table that determines resolution based on the number of 50 MHz clocks per twenty lines, and number of lines per frame.

Digitization of the analog video data signals occurs based on the n pixel clocks per line. Referring now to **FIG. 5**, the PLL 20, the VCO 50 generates the pixel clock
25 signal, and the microcontroller 16 sets the counter 22 to generate a feedback pulse (line

advance signal) once every n pixel clocks. Once n is selected, the PLL automatically adjusts to produce a line advance signal frequency corresponding to H_{sync} , and a pixel clock signal having a frequency of n times the line advance frequency.

The PLL works by the phase comparator 46 receiving the H_{sync} signal from the delay device 18 through conductor 44, and receiving the feedback pulse signal through the feedback loop 52. The phase comparator 46 compares the frequencies of the H_{sync} and the feedback pulse signal, generating an output voltage that is a measure of their phase difference. If the feedback pulse frequency does not equal the H_{sync} frequency, the phase difference signal causes the VCO pixel clock frequency to deviate so that the feedback pulse frequency of the counter 22 deviates toward the H_{sync} frequency.

Referring again to **FIG. 5**, the feedback pulse signal (line advance signal) of the counter 22 is directed to the ASIC 26 and 27 through a conductor 53, and the pixel clock signal of the VCO 50 is directed to the ASIC 26 and 27 and the A/D converter 24 through conductor 54. The line advance signal and V_{sync} signal (frame advance signal) are conditioned to be one clock pulse in duration, through the use of a pulse edge detection circuit or the like.

The A/D converter 24 samples (reads) the instantaneous voltage value of the analog video data signal at the leading edge of each of the pixel clocks, thereby generating a series of sampled data signal values. The A/D converter 24 then quantizes the sampled values by matching each value to one of a series of preselected voltage amplitude levels, which have corresponding numerical values. These numerical values are then represented digitally and coded to establish 8-bit data for each of the colors red, green and blue.

Referring now to **FIGS. 5 and 7**, the three eight-bit color data signals are input through the three respective color data signal channels 56a, 56b, 56c to the pixel value

calculator 97. The output 101 of the pixel value calculator 97 is connected through bus 103 to the reference frame capture circuit 27.

Using the output of the reference frame capture circuit 27, the microcontroller 16 controls the capture of a reference frame from the output of the A/D converter 24. The captured reference frame is stored in WRAM 132 for eventual transmission to the LCD, DMD, or other display object 28. At the display object 28, the coded color data signal sets pixels to blank (black) or to a specific activated (non-black) status corresponding to the sampled voltage level.

Referring now to **FIG. 8**, the output of the reference frame capture circuit 27 is a capture switch 120 that is set to on to instruct the microcontroller 16 to capture a new reference frame, or is set to off to prevent the microcontroller 16 from doing so. The V_{sync} frame advance signal 58 generates a first inbound frame that is captured as the first reference frame and stored in stored frame memory in WRAM 132. The V_{sync} frame advance signal 58 generates a subsequent inbound frame that is compared by the pixel value comparator 115 pixel-by-pixel to the pixel values of the first reference frame. The pixel value comparator 115 compares the absolute value of the difference between the inbound pixel value and the reference pixel value to a threshold value input 110. If the absolute value of the difference between any of the corresponding inbound and reference pixel values exceeds the threshold value input 110, then the pixel value comparator 115 generates a binary "yes" setting the capture switch 120 to on.

Referring now to **FIGS. 7 and 8**, in one embodiment the pixel value calculator 97 determines the value of each pixel by grouping the twenty-four total bits of each pixel together in eight groups of individual red, green and blue bits. Each of these groups of three bits is passed through the "OR" gate 99a, and the results of all of the eight "ored" groups and the digital RGB data signals are multiplexed in the 4:1 multiplexer 99b to establish a value for each pixel. It is contemplated that in another embodiment, the pixel

value may be set in various other ways, including setting a separate value for one or each of the RGB digital data signals. In the latter case, the pixel value comparator 115 compares the absolute value of the difference between each of the RGB values of the inbound pixel and the reference pixel to the threshold value input 110. If the difference between any of the corresponding inbound and reference pixel RGB values exceeds the threshold value input 110, then the pixel value comparator 115 generates a binary "yes" setting the capture switch 120 to on.

Referring again to **FIG. 8**, the pixel value comparator 115 performs the pixel comparisons iteratively using the HPC 105 to step through every pixel in every line, and comparing the absolute value of the difference between each of the inbound pixel values and corresponding reference pixel values to the threshold value input 110. If the difference between any of the corresponding inbound and reference pixel values exceeds the threshold value input 110, then the capture switch 120 is set to on. After every pixel of every line of the inbound frame that triggered the capture has been completely processed, the capture switch 120 triggers the microcontroller 16 to capture a new reference frame. After capturing a new reference frame, the capture switch 120 is reset to off.

The entire process of capturing and comparing is repeated continually throughout the duration of the image conversion. The result is that the number of reference frames captured by the microcontroller 16 for storage in WRAM 132 and eventual display by display object 28 is a subset of the total number of inbound frames output by the A/D converter 24. Moreover, by selectively capturing an inbound frame only after determining that a preceding inbound frame exceeds a certain threshold of change, inbound frames whose pixel values are either static or that represent below-threshold changes that indicate phase noise or distortion can be eliminated.

Example Implementation

An example implementation of a method for reducing phase noise and distortion in a digitally converted image based on reference frame capture will now be described. Referring to **FIG. 9**, wherein a flow diagram of a reference frame capture method used in the reference frame capture circuit 27 in accordance with one embodiment of the present invention is illustrated. As shown, after advancing the pixel position 150 using the HPC 105, the pixel value comparator 115 compares the absolute value of the difference between the inbound and reference frame pixel values to a pre-selected threshold value 110. If the threshold value 110 is exceeded, then the capture switch 120 is set to on 155; otherwise it remains set to off. If the end of the current line of the inbound frame 160 hasn't yet been reached, then the pixel position is again advanced 150, and the pixel value comparison 115 is repeated. However, if the end of the current line has been reached, then the next inbound line is first obtained using the line advance signal 53. If the end of the inbound frame 165 hasn't yet been reached, then the pixel position of the newly obtained next inbound line is advanced 150, and the pixel value comparison 115 is repeated, and so on. If, however, the end of the inbound frame has been reached 165, then the next inbound frame is obtained using the frame advance signal 58. If the capture switch 120 is set on 170, then the newly obtained next inbound frame is captured as the new reference frame and stored 175 in stored frame memory in WRAM 132. The capture switch 120 is reset to off 180, and another inbound frame is obtained using the frame advance signal 58. Since the capture switch 120 is now set to off, then the pixel position of the first line in the newly obtained inbound frame is advanced 150, and the pixel value comparison 155 is repeated, this time by comparing the inbound pixels to the pixels of the newly captured reference frame.

Referring now to FIG. 10, wherein a tabulation of a series of inbound frames and lines and the corresponding pixel value comparisons and resulting actions is illustrated in accordance with one embodiment of the present invention. As shown, each line is comprised of pixel values that range in value from hexadecimal zero ("0") to 255 ("FF"), with each value corresponding to one of 255 shades of the colors red, green, and blue. The position of each pixel with a given line is indicated by the current value of the HPC 105. The threshold value in this example is pre-set to the value of 5. Lines 1-5 of frame 1 is stored as the first reference frame 175. The pixel values of the lines comprising inbound frame 2 are compared to the values of reference frame 1, however since none of the differences between the corresponding pixel values of the lines comprising frames 1 and 2 exceed the pre-set threshold of 5, no action results. For example, the pixels located in reference frame 1, Line 4, HPC 6 and inbound frame 2, Line 4, HPC 6 result in the pixel value comparison 115 as follows:

$$| 2 - 3 | = 1$$

Likewise the pixels located in reference frame 1, Line 5, HPC 7 and inbound frame 2, Line 5, HPC 7 result in the pixel value comparison 115 as follows:

$$| 3 - 3 | = 0$$

Since the difference of 1 and 0 do not exceed the threshold of 5, there is no change sufficient to trigger the capture of a new reference frame.

Examining the same relative pixel locations in inbound frame 3232, however, yields a different result. This time, the pixels located in reference frame 1, Line 4, HPC 6 and inbound frame 3232, Line 4, HPC 6 result in the pixel value comparison 115 as follows:

$$| 3 - FF | = FC$$

Likewise the pixels located in reference frame 1, Line 5, HPC 7 and inbound frame 3232, Line 5, HPC 7 result in the pixel value comparison 115 as follows:

$$| 3 - FF | = FC$$

Since the differences of FC do exceed the threshold of 5, the capture switch 120 is set on 155 to trigger a reference frame capture upon advancing to the next inbound frame. As shown, advancing to the next inbound frame 3233 results in the action of storing 175
5 frame 3233 as the new reference frame against which subsequent pixel value comparisons will be based.

As noted earlier, in one embodiment, the individual RGB values are used as the pixel values by the pixel value comparator 115. Referring now to FIG. 11, an example of pixel values for an inbound 201 and reference 202 (stored) pixel are shown in decimal notation. The pixel value comparator 115 generates comparisons for the red color 203, the green color 204, and the blue color 205. As can be seen, only the blue color 205 comparisons result in a value of decimal "113" that exceeds the pre-set threshold of 5. This is sufficient, however, to trigger the capture and storage of a new reference frame 175.

Accordingly, a novel method and apparatus is described for reducing phase noise and distortion in a digitally converted image using a captured reference frame. From the foregoing description, those skilled in the art will recognize that many other variations of the present invention are possible. Thus, the present invention is not limited by the details described. Instead, the present invention can be practiced with
20 modifications and alterations within the spirit and scope of the appended claims.

I Claim:

- 1 1. A method of displaying a digitally converted image comprising:
2 receiving a plurality of frames of digitized image data, each frame having a
3 plurality of pixel values;
4 capturing at least one reference frame into a frame buffer memory; wherein the
5 at least one reference frame is selected from the plurality of frames based on the pixel
6 values of each of the plurality of frames; and
7 transmitting the at least one captured reference frame to a display object.
- 1 2. The method of claim 1, wherein the capturing comprises:
2 storing a first one of the plurality of frames as a first reference frame in a frame
3 buffer memory;
4 iteratively comparing a subsequent one of the plurality of frames to the stored
5 reference frame until the difference between any of the plurality of pixel values of the
6 subsequent frame and the corresponding plurality of pixel values of the stored reference
7 frame exceed a pre-selected threshold value; and
8 storing a next subsequent one of the plurality of frames as a second reference
9 frame in the frame buffer memory.
- 1 3. The method of claim 2, wherein the pixel values comprise a numerical value for
2 each color of each pixel.
- 1 4. The method of claim 3, wherein the difference between any of the plurality of
2 pixel values is the difference between the numerical values for each color of each of the
3 corresponding pixels of the compared frames.

1 5. The method of claim 2, wherein the difference between any of the plurality of
2 pixel values of the compared frames exceeds a pre-selected threshold value when the
3 absolute value of the difference is greater than the pre-selected threshold value.

1 6. The method of claim 3 wherein the color for each pixel includes the colors red,
2 green, and blue.

1 7. An apparatus for displaying a digital image comprising:
2 an input for receiving a plurality of frames of digitized image data, each frame
3 having a plurality of pixel values;
4 a processor for storing a first one of the plurality of frames as a first reference
5 frame in a frame buffer memory, for iteratively comparing a subsequent one of the
6 plurality of frames to the reference frame until the difference between any of the plurality
7 of pixel values of the subsequent frame and the corresponding plurality of pixel values
8 of the first reference frame exceed a pre-selected threshold value, and for storing a next
9 subsequent one of the plurality of frames as a second reference frame in the frame
10 buffer memory; and
11 an output for transmitting the stored reference frames of data in frame buffer
12 memory to a display object.

1 8. The apparatus of claim 7, wherein the pixel values comprise a numerical value
2 for each of a plurality of colors of each pixel.

1 9. The apparatus of claim 8, wherein the plurality of colors for each pixel includes
2 red, green, and blue.

1 10. The apparatus of claim 8, wherein the difference between any of the plurality of
2 pixel values is the difference between the numerical value for each of the plurality of
3 colors for each of the corresponding pixels of the compared frames.

1 11. The apparatus of claim 8, wherein the difference between any of the plurality of
2 pixel values of the compared frames exceeds a pre-selected threshold value when the
3 absolute value of the difference is greater than the pre-selected threshold value.

1 12. A digital image display process comprising:
2 storing a first frame of data in a reference frame memory, the first frame of data
3 having a plurality of pixel values;
4 comparing a subsequent frame of data to the frame of data in reference frame
5 memory until the difference between any of the pixel values of the subsequent frame
6 and the corresponding pixel values of the frame of data in reference frame memory
7 exceed a pre-selected threshold value;
8 storing a next subsequent frame of data in a reference frame memory; and
9 transmitting the stored frames of data in reference frame memory to a display object.

1 13. The process of claim 12, wherein the difference between any of the pixel values
2 is the difference between a numerical value for each color of each of the corresponding
3 pixels of the compared frames.

1 14. The process of claim 13, wherein the difference between any of the pixel values
2 of the compared frames exceeds a pre-selected threshold value when the absolute
3 value of the difference is greater than the pre-selected threshold value.

1 15. A computer-readable medium having computer-executable instructions for
2 performing:

3 generating from an analog signal a plurality of frames of digitized image data,
4 each frame having a plurality of pixel values;

5 storing a first one of the plurality of frames as a reference frame in a frame buffer
6 memory;

7 iteratively comparing a subsequent one of the plurality of frames to the reference
8 frame until the difference between any of the plurality of pixel values of the subsequent
9 frame and the corresponding plurality of pixel values of the reference frame exceed a
10 pre-selected threshold value; and

11 storing a next subsequent one of the plurality of frames as a reference frame in
12 the frame buffer memory; and

13 transmitting the stored reference frames of data in frame buffer memory to a
14 display object.

1 16. A method of displaying a digitally converted image comprising:

2 generating from an analog signal a plurality of frames of digitized image data,
3 each frame having a plurality of pixel values;

4 selecting at least one the plurality of frames for display to a display object,
5 wherein the at least one frame is selected by:

6 storing a first one of the plurality of frames in a reference frame memory;

7 iteratively comparing a subsequent one of the plurality of frames to the
8 reference frame memory until the difference between any of the plurality of pixel
9 values of the subsequent frame and the corresponding plurality of pixel values of
10 the reference frame memory exceed a pre-selected threshold value; and
11 storing a next subsequent one of the plurality of frames in the reference
12 frame memory; and
13 transmitting the stored frames of data in the reference frame memory to the
14 display object.

ABSTRACT

A method for reducing phase noise and distortion in a digitally converted image in which only a selected subset of the video frames that represent the image are displayed. The selected subset is comprised of reference video frames, where a new reference frame is captured for display after determining that a pixel of an inbound video frame exceeds a certain threshold of change as compared to a corresponding pixel of a previously captured reference frame. The pixel comparison is performed by comparing corresponding numerical values representing each of the pixel's color values, red, green, and blue, or by comparing corresponding numerical values representing a composite color value. The threshold determination is performed by comparing the absolute value of the difference between each of the corresponding pixel values to a pre-selected change threshold value. After determining that the threshold has been exceeded, the next consecutive inbound frame is captured and stored in a frame buffer memory as a new reference frame. All of the stored reference frames are transmitted from the frame buffer memory for display to a display object in accordance with the display object's frame refresh rate. The threshold value is pre-selected to eliminate the intervening sub-threshold inbound frames causing the phase noise and distortion, which not only improves the quality of the displayed image but also reduces the total number of new frames that must be transmitted to the display object.

Fig. 1




Fig. 2




Fig. 3





Fig. 4



[illegible][illegible]

Fig. 6




Fig. 7




FIG. 8

27




FIG. 9




FIG. 11

INBOUND PIXEL ⁽²⁰¹⁾

R	245
G	200
B	197

REFERENCE PIXEL ⁽²⁰²⁾
(STORED) PIXEL

R	241
G	204
B	200

75

203 - R	245 -	241 = 4	→ FALSE
204 - G	200 -	204 = 4	→ FALSE
205 - B	87 -	200 = 113	→ TRUE

DECLARATION AND POWER OF ATTORNEY FOR PATENT APPLICATION

As a below named inventor, I hereby declare that:

My residence, post office address and citizenship are as stated below, next to my name.

I believe I am the original, first, and sole inventor (if only one name is listed below) or any original, first, and joint inventor (if plural names are listed below) of the subject matter which is claimed and for which a patent is sought on the invention entitled

METHOD AND APPARATUS FOR NOISE REDUCTION USING CAPTURED IMAGES

the specification of which ☒ is attached hereto.
☐ was filed on _____ as _____
United States Application Number _____
or PCT International Application Number _____
and was amended on _____
(if applicable)

I hereby state that I have reviewed and understand the contents of the above-identified specification, including the claim(s), as amended by any amendment referred to above. I do not know and do not believe that the claimed invention was ever known or used in the United States of America before my invention thereof, or patented or described in any printed publication in any country before my invention thereof or more than one year prior to this application, that the same was not in public use or on sale in the United States of America more than one year prior to this application, and that the invention has not been patented or made the subject of an inventor's certificate issued before the date of this application in any country foreign to the United States of America on an application filed by me or my legal representatives or assigns more than twelve months (for a utility patent application) or six months (for a design patent application) prior to this application.

I acknowledge the duty to disclose all information known to me to be material to patentability as defined in Title 37, Code of Federal Regulations, Section 1.56.

I hereby claim foreign priority benefits under Title 35, United States Code, Section 119(a)-(d), of any foreign application(s) for patent or inventor's certificate listed below and have also identified below any foreign application for patent or inventor's certificate having a filing date before that of the application on which priority is claimed:

Prior Foreign Application(s):

APPLICATION NUMBER	COUNTRY (OR INDICATE IF PCT)	DATE OF FILING (day, month, year)	PRIORITY CLAIMED UNDER 37 USC 119
			<input type="checkbox"/> No <input type="checkbox"/> Yes
			<input type="checkbox"/> No <input type="checkbox"/> Yes
			<input type="checkbox"/> No <input type="checkbox"/> Yes

I hereby claim the benefit under Title 35, United States Code, Section 119(e) of any United States provisional application(s) listed below:

APPLICATION NUMBER	FILING DATE

Appendix A

I hereby appoint BLAKELY, SOKOLOFF, TAYLOR & ZAFMAN LLP, a firm including: William E. Alford, Reg. No. 37,764; Farzad E. Amini, Reg. No. 42,261; William Thomas Babbitt, Reg. No. 39,591; Carol F. Barry, Reg. No. 41,600; Jordan Michael Becker, Reg. No. 39,602; Lisa N. Benado, Reg. No. 39,995; Bradley J. Bereznak, Reg. No. 33,474; Michael A. Bernadicou, Reg. No. 35,934; Roger W. Blakely, Jr., Reg. No. 25,831; R. Alan Burnett, Reg. No. 46,149; Gregory D. Caldwell, Reg. No. 39,926; Andrew C. Chen, Reg. No. 43,544; Thomas M. Coester, Reg. No. 39,637; Donna Jo Coningsby, Reg. No. 41,684; Florin Corie, Reg. No. 46,244; Dennis M. deGuzman, Reg. No. 41,702; Stephen M. De Klerk, Reg. No. P46,503; Michael Anthony DeSanctis, Reg. No. 39,957; Daniel M. De Vos, Reg. No. 37,813; Sanjeet Dutta, Reg. No. P46,145; Matthew C. Fagan, Reg. No. 37,542; Tarek N. Fahmi, Reg. No. 41,402; George Fountain, Reg. No. 37,374; James Y. Go, Reg. No. 40,621; James A. Henry, Reg. No. 41,064; Willmore F. Holbrow III, Reg. No. P41,845; Sheryl Sue Holloway, Reg. No. 37,850; George W. Hoover II, Reg. No. 32,992; Eric S. Hyman, Reg. No. 30,139; William W. Kidd, Reg. No. 31,772; Sang Hui Kim, Reg. No. 40,450; Walter T. Kim, Reg. No. 42,731; Eric T. King, Reg. No. 44,188; Erica W. Kuo, Reg. No. 42,775; George B. Leavell, Reg. No. 45,436; Gordon R. Lindeen III, Reg. No. 33,192; Jan Carol Little, Reg. No. 41,181; Kurt P. Leyendecker, Reg. No. 42,799; Joseph Lutz, Reg. No. 43,765; Michael J. Mallie, Reg. No. 36,591; Andre L. Marais, under 37 C.F.R. § 10.9(b); Paul A. Mendonsa, Reg. No. 42,879; Clive D. Menezes, Reg. No. 45,493; Chun M. Ng, Reg. No. 36,878; Thien T. Nguyen, Reg. No. 43,835; Thinh V. Nguyen, Reg. No. 42,034; Dennis A. Nicholls, Reg. No. 42,036; Daniel E. Ovanezian, Reg. No. 41,236; Kenneth B. Paley, Reg. No. 38,989; Marina Portnova, Reg. No. P45,750; William F. Ryann, Reg. No. 44,313; James H. Salter, Reg. No. 35,668; William W. Schaal, Reg. No. 39,018; James C. Scheller, Reg. No. 31,195; Jeffrey Sam Smith, Reg. No. 39,377; Maria McCormack Sobrino, Reg. No. 31,639; Stanley W. Sokoloff, Reg. No. 25,128; Judith A. Szepesi, Reg. No. 39,393; Vincent P. Tassinari, Reg. No. 42,179; Edwin H. Taylor, Reg. No. 25,129; John F. Travis, Reg. No. 43,203; Joseph A. Twarowski, Reg. No. 42,191; Thomas A. Van Zandt, Reg. No. 43,219; Lester J. Vincent, Reg. No. 31,460; Glenn E. Von Tersch, Reg. No. 41,364; John Patrick Ward, Reg. No. 40,216; Mark L. Watson, Reg. No. P46,322; Thomas C. Webster, Reg. No. P46,154; and Norman Zafman, Reg. No. 26,250; my patent attorneys, with offices located at 12400 Wilshire Boulevard, 7th Floor, Los Angeles, California 90025, telephone (503) 684-6200, and Justin M. Dillon, Reg. No. 42,486; my patent agent, Dov Rosenfeld, Reg. No. 38,687; and James R. Thein, Reg. No. 31,710; with full power of substitution and revocation, to prosecute this application and to transact all business in the Patent and Trademark Office connected herewith.